

NA7004 Addendum Sheet

Thank you for purchasing Marantz's product. When you operate the unit, please read the User Guide and this sheet.

📄 page 22 : **Change**

Menu map

Setting items	Detailed items		Description
Network	Party Mode	Party Mode Function	Starts or stops the party mode.
		Zone Management*	Enable/disable the party mode.
	Other Network	Zone Management*	Display and control a maximum of 10 devices that are connected to the same network.

* Item name has been changed.

Addition

Party Mode Function

The same network audio (Internet radio, music server or iPod) can be played on multiple products equipped with the Party Mode function and connected in a network.

The party mode consists of one organizer and up to four attendees.

When one unit starts the party mode as the organizer, up to four devices on which the party mode function is activated automatically participate in the party as attendees. "Party Mode Function" must be set to "ON" ahead of time in order to use the party mode function.

❑ Setting the Party Mode Function

- 1 Press [MENU].
The Menu appears on the display.
- 2 Use Δ/∇ to select "Network" – "Party Mode" – "Party Mode Function", then press [ENTER/MEMO], <ENTER> or \triangleright .
"P-Mode Function" menu appears.
- 3 Use Δ/∇ to select "On" or "Off", then press [ENTER/MEMO], <ENTER> or \triangleright .

On	Enable party mode function.
Off	Disable party mode function.

❑ Starting the party mode as the organizer

- 1 Press [MENU].
The Menu appears on the display.
- 2 Use Δ/∇ to select "Network" – "Party Mode" – "Start Party", then press [ENTER/MEMO], <ENTER> or \triangleright .
 - An error message is displayed when you are not connected to a network.
 - The input source automatically switches to "Music Server" and the attendees are automatically selected.
- 3 Play the desired station.

Canceling the party mode

- 1 Press [MENU].
The Menu appears on the display.
- 2 Use Δ/∇ to select "Stop Party", then press [ENTER/MEMO], <ENTER> or \triangleright .
"Exit Party Mode?" is displayed on the menu screen.
- 3 Use Δ/∇ to select "Yes", then press [ENTER/MEMO], <ENTER> or \triangleright .
"Attendee P.Off?" is displayed.
- 4 Use Δ/∇ to select "Yes" or "No", then press [ENTER/MEMO], <ENTER> or \triangleright .

Yes	The power of the attendees is turned off and the party mode is canceled.
No	The party mode is canceled without turning off the power of the attendees.

❑ Participating in the party mode as an attendee

- When the organizer starts the party mode, up to four attendees are selected automatically. No operation is required.
- When a device becomes an attendee, **Party Mode Attendee** appears on the display. The input source automatically switches to "Music Server" and the same network audio as on the organizer is played.
- If there are fewer than four attendees, a device can join the party mode after it has started. To participate in the party mode, perform the operation described below.

- 1 Press [MENU].
The Menu appears on the display.
- 2 Use Δ/∇ to select "Network" – "Party Mode" – "Start Party", then press [ENTER/MEMO], <ENTER> or \triangleright .
 - An error message is displayed when you are not connected to a network.

Selecting tracks from attendees

When the party mode starts, "Party Mode Attendee" appears on the attendee's display, after which the organizer's playback information appears.



Party Mode Display Attendee Display

- 1 Press \triangleleft to display the organizer's input source.
- 2 Press Δ/∇ to select the input source, then press [ENTER/MEMO], <ENTER> or \triangleright .
- 3 Press Δ/∇ to select the item you want to play, then press [ENTER/MEMO], <ENTER> or \triangleright .

Canceling the party mode

- 1 Press [MENU].
The Menu appears on the display.
- 2 Use Δ/∇ to select "Stop Party", then press [ENTER/MEMO], <ENTER> or \triangleright .
"Exit Party Mode?" is displayed on the menu screen.
- 3 Use Δ/∇ to select "Yes", then press [ENTER/MEMO], <ENTER> or \triangleright .
In this case, the other devices remain in the party mode.



"Last.fm", "Napster" and "USB" are not available in the Party Mode.
There can only be one organizer in the network. To form a new party mode, first cancel the current party mode.

Addition

Zone Management Function

The "Device Control" item was added to the "Network" – "Other Network" – "Zone Management" menu.
With "Device Control", the network functions (Internet radio etc) of the device selected in step 3 can be controlled using this unit.

- 1 Press [MENU].
The Menu appears on the display.
- 2 Press Δ/∇ to select "Network" – "Other Network" – "Zone Management" from the menu, and then press [ENTER/MEMO], <ENTER> or \triangleright .
 - The status of up to 10 other devices connected to the same network can be displayed.
- 3 Press Δ/∇ to select the device, and then press [ENTER/MEMO], <ENTER> or \triangleright .
- 4 Press Δ/∇ to select "Device Control", and then press [ENTER/MEMO], <ENTER> or \triangleright .
The network menu of the other person is displayed on this unit's display.
- 5 Press Δ/∇ , [ENTER/MEMO], <ENTER> or \triangleright to select the desired track.
 - For information about how to operate, see the User Guide provided with the product.



The zone management function can only be used on a combination of devices that are equipped with the zone management function.

NOTE

The volume of the selected device can be controlled using this unit, but the volume level is not displayed. Be careful not to increase the volume too high.