

SR4021

STEREO RECEIVER



The ideal answer for those who want Marantz-quality sound reproduction of audio and video sources. Complete with A/V switching and multiple video outputs, the SR4021 functions as the heart of a "home theater 2.0" system, a secondary zone, or a main music system. Flexibility characterizes the SR4021. Not only does it boast 80 watts continuous output from each channel of its stereo amplifier, it includes all the video switching capability to fully integrate a home entertainment system that includes both audio and video sources. From its extruded aluminum front panel to the preamp output/main amp input jacks, the SR4021 is built to support a wide variety of system configurations. There's a front panel infrared sensor and three pre-programmed code sets that make this component well-suited for remote zone use. Two sets of loudspeaker outputs, a detachable AC cord, and a Marantz System Remote add the final touches for all-in-one utility, and easy placement almost anywhere.

- 80 watts x 2 (into 8 ohms)
- All discrete amplifier stages
- Pre-out/Main-in terminals
- Phono input with built-in phono equalizer
- 4 dedicated audio inputs
- Video switching capabilities
- 3 Audio/Video inputs
- Triple IR code sets for multiple use
- Source direct mode
- Detachable power cord
- Electronic tone controls
- Display dimmer/off
- AM/FM Tuner with 30 presets
- Headphone output
- Station naming capabilities
- 1 switched and 1 un-switched AC outlets
- Speaker A and B
- Direct IR Flasher Input
- Frequency direct tuning
- D-BUS (RC-5 In/Out) remote connection
- Sleep timer
- Marantz system control remote
- Aluminum front panel
- Three year limited warranty

3 YR WARRANTY

marantz®

LIFE AMPLIFIED™

SR4021

FEATURES

Number of Channels	2
Power Output/Channel (20Hz - 20kHz) @ 8W	80 W
Front Panel	Aluminum
Power Transformer	EI
Discrete Amplifier Stage	¥
Balance Adjustment	¥
Tone Control (Bass/Treble)	¥
Source Direct	¥
Speaker A/B	¥
Sleep Timer	¥
Preset Station	30
Multiple IR Code Set	3
Detachable AC Cord	¥
IN/OUTPUTS	
AUDIO	
Analog L&R In	8
Phono In	¥
Main Amplifier In	¥
Analog L&R Out	3
Pre-Amplifier Out	¥
Headphone Out	¥
VIDEO	
Composite In	3
Composite Out	4
OTHERS	
D-Bus Remote (RC-5) In/Out	1/1
IR Flasher In	1
External Control (RS232C)	-
AC Outlets (Switched/Unswitched)	1/1

SPECIFICATIONS

AUDIO SECTION	
THD (40Hz - 20kHz, 8.)	< 0.08%
Input Sensitivity/Impedance	200 mV/47kΩ
Frequency Response (+/- 3 dB)	20Hz - 20kHz
S/N Ratio	95 dB
TUNER SECTION FM	
Frequency Range	87.5 - 108.0MHz
S/N Ratio (Mono/Stereo)	70/65 dB
Distortion (Mono/Stereo)	0.2/0.3 %
Stereo Separation	40 dB (1kHz)
TUNER SECTION AM	
Frequency Range	520 - 1710kHz
Usable Sensitivity	Loop 400 _V
S/N Ratio	50 dB
GENERAL	
Color	Black
Remote Control	Device Remote RC4021SR
Power Requirement	AC 120V 60Hz
Power Consumption	220 W
Dimensions (Inches) W x H x D	17 5/16" x 6 1/2" x 15 1/2"
Weight (lbs.)	25.8

*All specifications, dimensions and weights are subject to change without notice.

D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

© 10/06 Marantz America, Inc. ¥ 100 Corporate Drive ¥ Mahwah, New Jersey 07430 ¥ 201-762-6500 ¥ www.marantz.com