marantz



NR1504

SLIM DESIGN NETWORK AV RECEIVER



















In addition to a host of connectivity options and DTS-HD, Dolby True HD processing, this receiver now has network streaming capability. Now you can enjoy Apple lossless, Gapless, FLAC HD 192/24, AirPlay, as well as services such as last.fm and Spotify, and Internet radio. Fans of devices such as camcorders and a variety of smartphones or tablets will also love the front panel HDMI input for easy and instant video / music enjoyment. 85W are outputted to each of the 5 channels and can be used for a simple stereo set-up or to run a full 5.1 system, creating spectacular surround sound and converting your living room into a sensational cinema. It also includes a Setup Assistant, Audyssey MultEQ and Microphone, all is there for easy, perfect setup. Its total of six HDMI inputs handle a multitude of digital sources, so you can easily hook-up your satellite box, BD/DVD player, game console and camcorder... all at the same time. And all with just one HDMI cable connected to your screen. It all adds up to fabulous sound, great video quality and elegant slim-line appearance.

Main Features

- Dolby TrueHD and dts-HD Master Audio
- 5ch discrete power amplifier, 85 W per channel
- Pure Direct
- HDMI: 5+1 in / 1out (3D, ARC, Deep Color)
- M-DAX2 audio expander for compressed music
- M-Xport for Bluetooth with optional RX101
- Network Audio and JPEG streaming
- MP3, WAV, AAC, FLAC, WMA, Lossless, FLAC192/24 (HD)
- Gapless Playback
- Spotify, last.fm, Flickr, Internet Radio support
- iPod/iPhone compatible USB, iPad charging
- New Marantz Remote App for iOS and Android devices

EAN

EU	NR1504/N1B	4951035050545	Black
	NR1504/N1SG	4951035050552	Silver-Gold
UK	NR1504/T1B	4951035050545	Black
	NR1504/T1SG	4951035050552	Silver-Gold

www.marantz.eu





NR1504

SLIM DESIGN NETWORK AV RECEIVER



FEATURES	NR1504
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	•/•/•/•
Dolby Digital Plus / Dolby TrueHD	• / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
Network	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
FLAC HD 192/24	•
WAV 192/24	•
ALAC 96/24	•
Gapless playback	• (FLAC, WAV)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio (vTuner)	•
Spotify*	•
last.fm*	•
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet	•
OTHERS	
Bluetooth audio via RX101	optional
Auto speaker setup by microphone	Audyssey MultEQ
Audyssey Dynamic EQ / Dynamic Volume	• / •
HDMI path though on stand-by	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: Hybrid GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian)	•
Variable cross over	•
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3/1
HDMI In / Out	5+1 / 1 (1.4)
AUDIO	
Analogue In / Out	3/0
Digital Optical In / Out	1/0
Digital Coaxial In / Out	1/0
Multichannel Pre Out	• (2.1)
Subwoofer Out	1
Headphone Out	1
OTHER	
M-XPort for RX101	•
Marantz remote bus	•
Front HDMI Input	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Works with iPhone	• / • / •
ADDICATE ADDICATE	
SPECIFICATIONS	
Number of poweramps	5
	5
Number of poweramps	5 85 W
Number of poweramps Power Output per channel	·
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive	85 W
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive	85 W 60 W
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	85 W 60 W 50 W
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio	85 W 60 W 50 W
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio AM/FM Tuner	85 W 60 W 50 W
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio AM/FM Tuner GENERAL	85 W 60 W 50 W 98 dB
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio AM/FM Tuner GENERAL Available colors: Black / Silver-Gold	85 W 60 W 50 W 98 dB
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz. 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio AM/FM Tuner GENERAL Available colors: Black / Silver-Gold System Remote Control	85 W 60 W 50 W 98 dB •
Number of poweramps Power Output per channel 6 ohm, 1 kHz, 1%, 1ch Drive 6 ohm, 1 kHz, 0.7%, 2ch Drive 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive Audio Signal to Noise Ratio AM/FM Tuner GENERAL Available colors: Black / Silver-Gold System Remote Control Power Consumption in W	85 W 60 W 50 W 98 dB • RC020SR 180 0.2 W (Standby) /



Convenient front panel HDMI input along with a USB port



* This feature is not available in all countries.

AirPlay lets you stream audio content from your iPod, iPhone and iPad $\,$

www.marantz.eu Ivosi