

marantz®

SR7009

AV RECEIVER WITH WI-FI & BLUETOOTH®



The new SR7009 builds on last year's SR7008 with no less than nine amplifier channels, each with 125W (8ohms, 20 Hz - 20K Hz, THD 0.08%) per channel of pure power. Imagine: nine strategically-located speakers with audio processing capabilities that go even further - handling up to 11.2 channels to fully support Audyssey DSX, DTS Neo:X 11.1, as well as the latest decoding technology Dolby Atmos® - you will experience the absolute ultimate in surround sound, as well as preparing your system for 3D sound. What's more, thanks to Audyssey MultEQ XT32 and Sub EQ HT, the highest grade of Audyssey technologies, you get an even more accurate calibration of each speaker to guarantee that every seat in the room is a 'sweet spot' for audio. The SR7009 has Wi-Fi and Bluetooth built in and it supports Apple® lossless, Gapless, FLAC HD 192/24 and even DSD and AIFF network streaming. Spotify Connect®, Pandora®, SiriusXM™, and AirPlay® audio streaming are on board too. But we haven't changed everything. We've kept the staggering impact of audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail, and sensational depth: all thanks to the use of current feedback technology, HDAM pre-amplification and, of course, the 125W (8ohms, 20 Hz - 20K Hz, THD 0.08%) for each of those nine channels. Imagine enjoying this exceptionally superior audio performance for all your music and movie sources. The eight HDMI (4k/60Hz pass through / scaling) inputs and the two HDMI output sockets for the main room and a third dedicated for multi-room application handle almost all of today's Ultra HD formats. The SR7009 also includes the ECO mode and Smart Select. And to get it all up and running effortlessly, there's a handy Setup Assistant. Enough said?

Main Features

- Wi-Fi and Bluetooth built in
- Dolby Atmos
- Dolby TrueHD and DTS HD Master Audio
- 9ch discrete power amplifier, 125W (8ohms, 20 Hz - 20K Hz, THD 0.08%) per channel
- 11.2ch signal processing and 13.2 Pre-out (with 2 independent subwoofers)
- Current Feedback circuitry with Marantz New HDAM
- Audyssey MultEQ XT32, Sub EQ HT, LFC
- Audyssey DSX; dts-Neo:X (11.1ch)
- Latest HDMI version with 4k 60Hz 4:4:4 resolution
- 7+1 HDMI in / 3 out (4k 60Hz, 4:4:4, 3D, ARC, Deep Color)
- HDMI scaling 1080p, 4k 50/60Hz
- MP3, WAV, AAC, WMA, AIFF
- HD Audio streaming: FLAC 192/24, DSD, ALAC
- Gapless Playback
- Spotify Connect*, Pandora, SiriusXM, Flickr, Internet Radio support
- Phono (MM) input
- Setup Assistant and advanced GUI
- Big trapdoor design; Aluminum front panel
- Marantz Remote App for iOS® and Android® devices
- ECO mode

UPC

NA SR7009/U1B 6-99927-22135-5 Black

DOLBY ATMOS®

Wi-Fi
CERTIFIED

Bluetooth

HDMI 7+1 in
3 out

4K HD
VIDEO

PC AUDIO
STREAMING

Spotify

PANDORA

SiriusXM
INTERNET RADIO

dts
Neo:X | 11.1

AUDYSSEY
DSX
LFC

AUDYSSEY
MULTEQ XT32

isf
ccc

us.marantz.com



because music matters

SR7009

AV RECEIVER WITH WI-FI & BLUETOOTH



FEATURES	SR7009
MULTI-CHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD	• / •
Dolby Atmos	•
Audyssey DSX	•
dts-Neo:X (11.1ch)	•
Multi-channel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
Photo streaming (JPEG)	•
AirPlay audio streaming	•
Windows PlayTo / Windows 8/RT compatible	• / •
Internet Radio/ Spotify Connect/ Pandora/ SiriusXM*	• / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna)
CONVENIENT AND SOUND	
FM / AM Tuner	• / •
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
High grade audio components	•
Bluetooth	•
Auto speaker setup by microphone	Audyssey MultEQ XT32/Sub EQ HT/ LFC
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion	CVBS > HDMI; Comp > HDMI
Video processing	>1080p, 4k 50/60Hz
ISF Certification	•
HDMI pass-through on stand-by	•
3D video pass-through / Audio Return Channel	• / •
On Screen Display: Advanced GUI	•
GUI overlay on HDMI	•
Setup Assistant (English, French, Spanish)	•
Smart Select	4 presets
Variable cross over	•
Multi-room zones	3
Optimized Bass Redirection	•

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + zone)
AUDIO	
Analogue In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multi-channel Pre Out	• (13.2)
Subwoofer Out	2
Zone audio preout	•
7.1 multi-channel input	•
OTHERS	
Gold-plated terminals	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting)	•
Multi-Room Speaker Terminal	Surround Back assignable
RS232 control	•
IR Flasher In	•
DC Trigger output	•
Marantz remote bus	•
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
SPECIFICATIONS	
Number of poweramps	9
Power Output per channel	
Maximum Power output per channel	235 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	165 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	125 W
Audio Signal to Noise Ratio	98 dB
GENERAL	
System Remote Control	RC026SR
Power Consumption in W	710
Power Consumption No-Sound (ECO ...on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in inches	17.32 x 15.79 x 7.28
Weight in lbs.	30.43

* This feature is not available in all countries.

Manufactured under license from Dolby Laboratories. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.