

marantz®



CD6002 – CD Player

The much praised PM6002 proved to be a more than excellent integrated amplifier over the past year. This amplifier has technologies based on the famous OSE amplifier series, and has taken integrated stereo amplifying a new level of excellence. With 2x 45W output, fast current delivery, customised audio components, including 2x 10000 μ F main capacitors and a large Toroidal Transformer, the PM6002 gives an even tighter bass, clearer stereo images, and a wider sound stage than the more expensive products on the market. Of course, original features such as 6-line audio input including Phono, two-pair gold plated speaker connection with the convenience of bi-wiring connection are still available. Twinned with the CD6002, for the music lover who wants nothing but the best performance, it is a match made in heaven.



because music matters

marantz®



FEATURES		CD6002	SPECIFICATIONS	
Disc Capacity		1	Mechanism	KSS-213CCM
CD Compatibility: CD / CD-R/RW / SA-CD / WMA / MP3		o/o/-/o/o	Decoder	TC94A70FG
SA-CD compatibility: Multi channel / stereo		-/-	D/A Conversion	Multi-bit, Delta-Sigma
CD-Text / SA-CD Text / ID3 Tag/ WMA Meta Tag		o/-/o/o	DAC IC	CS4398
High Grade Audio Components		o	Digital Filter	CS4398
Customized Components		o	Noise Shaper	CS4398
Symmetric circuit layout		o	Low Pass Filter stage	HDAM
Power Transformer: Toroidal / EI		-/o	Output Buffer	HDAM
HDAM version		CF	Headphone amp	NJM2068
Shotky diodes		o	Frequency Response	20Hz- 20 KHz
Zero Impedance Matching joint (copper)		-	Dynamic Range	100dB
Separated rectifier circuit for analogue and digital circuitry		o	Signal to Noise Ratio	110
Digital out off / Audio EX Mode		-/o	Total Harmonic Distortion	0.002
Display: Dimmer / Off		-/o	Channel Separation	110
Headphone: Standard / Buffer / Current feedback		-/o/-	GENERAL	
Copper plated chassis		-	Available colors: Gold/Silver/Black/Silver-Gold	-/o/o/-
Extra metal plate for chassis strengthening		o	Metal Front Panel	o
PLAYBACK			Remote Control	RC001CD
Program Play		30	Power Consumption in W	19
Auto Music Scan (AMS)		o	Standby Consumption in W	0.6
Repeat: track/program/A-B		o/o/o	Detachable Power Cable	o
Random Play		o	Maximum Dimensions (W x D x H) in mm	440x283x87
Peak Search		o	Weight in kg	4.7
Edit Recording		o		
Pitch Control		o		
Start Sound Mode for SA-CD		-		
Quick Replay		o		
INPUTS/OUTPUTS				
Analogue Out (Cinch)		2ch		
Digital Optical Out		1		
Digital Coaxial Out		1		
Gold plated Cinch		o		
USB		-		
D-Bus		o		
Headphone Out		o		
Headphone Volume Control		o		



Design and specifications are subject to change by Marantz without notice.

www.marantz.eu