

marantz®



NR1501 - Slim Design AV Receiver

The NR1501 slim-line AV Receiver in this year's line-up offers a host of connectivity options. The NR1501 has on-board decoders for both standard and high-definition audio such as DTS-HD and Dolby TrueHD, while its four HDMI 1.3a inputs handle a multitude of digital sources, so you can easily hook-up your satellite box, BD/DVD player, game console and camcorder... all at the same time. With just one HDMI cable connected to your screen. Fans of portable media players like iPods will love the front audio input for easy connection. The 7x 50W can be used for a simple stereo set-up but is also powerful enough to run a full 7.1 system, creating spectacular surround sound and converting your living room into a sensational cinema. MRAC auto set-up using a microphone makes installation fast and easy - even for non-technical users. It all adds up to fabulous sound, great video quality and elegant slim-line appearance.

Main Features

- Slim height cabinet
- 7x 50 Watts RMS
- Dolby TrueHD, DD+, DTS-HD
- Automatic speaker setup by MRAC
- Built-in FM/AM tuner with RDS
- 4in / 1out HDMI v1.3

because music matters



SPECIFICATIONS	NR1501		
MULTICHANNEL SURROUND		Variable cross over	o
THX Ultra II / Select II	-/-	Lip sync control	-
THX Surround EX	-	Multiroom zones	-
DTS HD / DTS 5.1 / DTS ES / DTS 96/24	o/o/o/o	Front flap	-
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / Dolby Pro-LogicIIz	o/o/o/o	Discrete RC coding (Main-/Multiroom)	o/-
Audyssey DSX	-	INPUTS/OUTPUTS	
Dolby Virtual Speaker / Neural Surround	-/-	VIDEO	
Multichannel Stereo	-	Composite In/Out	3/2
HT-EQ / Re-EQ	o/-	Component In/Out	3/1
DSD from SACD via HDMI	-	HDMI In/Out (version x.x)	4/1 (1.3a)
Dolby Headphone	-	Multiroom Video Out: Composite/S-Video/Component	-/-/-
Compressed audio enhancer: MDAX / MDAX2	-/-	AUDIO	
SURROUND ENHANCEMENTS		Analogue In/Out	5/1
Current Feedback Topology	-	Balanced In/Out	-/-
Hyper Dynamic Amplifier Modules (HDAM)	-	Phono MM In	-
Pure Direct	o (Source Direct)	Digital Optical In/Out	2/0
Power Transformer: Toroidal/EI	-/o	Digital Coaxial In/Out	1/0
High Grade Audio Components	-	Multiroom Out: analog/digital	-/-
Chassis: Copper plated / Metal	-/o	Multichannel Pre-Out/Main In	o(0.1ch)/-
NETWORK		Subwoofer Out	1
DLNA certified	-	7.1 Multichannel input	-
UPnP certified	-	OTHER	
Network Audio: MP3/WAV/AAC/FLAC/WMA	-	M-XPoort for RX101	-
Network static video (JPEG)	-	Speaker terminal: Gold plated screw/regular screw	-/o
Network video	-	Number of terminals	7
Internet radio: direct/external media player	-	Speaker A/B	-
vTuner/Napster/last.fm	-	Height speaker terminal	-
WiFi: integrated/external access point	-	Bi-amp drive (5.1 setting)/Speaker C	-/-
Ethernet	-	Marantz remote bus	o
IP Control	-	IR Receiver In / Emitter Out	-/-
Apple APP control by iPhone/iPod touch	-	IR Flasher In	-
OTHERS		Network: IP-control/update	-/-
Bluetooth audio via RX101	-	RS-232c (control/update)	-
Auto speaker setup	MRAC	DC Triggers	-
Audyssey Dynamic EQ/Dynamic Volume	-/-	Front Inputs: Analogue audio / Composite / Digital Audio (opt.) / HDMI/USB	o(3.5mm jack)/-/-/-
Video Conversion	CVBS > HDMI; Comp > HDMI	USB Audio/Made for iPod/Works with iPhone	-/-/-
Interlace / progressive conversion	-	SPECIFICATIONS	
Analogue to HDMI scaling	o	Power output (8/6 ohm RMS / 20Hz - 20kHz, 0,08%)	50/60 Watts
HDMI to HDMI scaling	-	70% Guarantee	-
Videoprocessing	-	Audio Signal to Noise Ratio	100dB
Picture adjust/noise reduction	-/-	FM Tuner	o
HDMI path-through on standby	-	GENERAL	
Deep Color pass through	o	Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/o
3D video pass through	-	Metal Front Panel	o
Audio Return Channel (ARC)	-	Backlit system remote control	RC006SR
CEC	-	Pre-programmed/Learnable/LCD Display	o/-/-
Front panel cursor control	o	Power Consumption in W	250W
On Screen Display: GUI / OSD	-/o	Standby Consumption in W	0.5W
		Detachable power cable	o
		Maximum Dimensions (W x D x H) in mm	440 x 376 x 105
		Weight in kg	8.6

because music matters