

# marantz®



## **RX9001 – Network Extender**

The RX9001 makes sure that you are in complete control of your entire in-house installation and gets the maximum out of your RC9001 remote controller. This extremely flexible network extender has a multitude of advanced connectivities: 4 addressable IR-ports, 4 RS232 serial interface, 4 relay outputs, 4x input power sensors and 1x voltage output, all packed into a solid 19 inch rack mountable housing. The RX9001 is able to operate in a wired network via standard CAT5-cable and supports DHCP and fixed IP-addresses for flexible and easy network configuration.

**because music matters**

# marantz®



| FEATURES                           | RX9001           |
|------------------------------------|------------------|
| System Control via CAT5 / Wireless | o/-              |
| Customization via Webserver        | o                |
| Network mode                       | DHCP, Fixed IP   |
| Addressable IR Emitter outputs     | 4                |
| Adjustable IR output level         | o                |
| IR code range                      | 25kHz - 1Mhz     |
| RS232 serial interface             | 4                |
| Relay outputs                      | 4 (max 48V / 2A) |
| DC Output                          | 1 (5V / 0.3A)    |
| Power sense input                  | 4 (4 - 30V)      |
| Status indication                  | 19 LED           |
| ACCESSORIES                        |                  |
| AC adaptor                         | 5V DC / 2A       |
| Crossover configuration cable      | o                |
| IR Emitter                         | 2x Dual IR       |
| Mini-jack IR cable                 | 2                |
| Rackmount kit                      | o                |
| GENERAL                            |                  |
| Colour: Black                      | o                |
| Dimensions (W x H x L) in mm       | 428 x 46 x 240   |
| Weight in kg                       | 1.75             |

Design and specifications are subject to change by Marantz without notice.

[www.marantz.eu](http://www.marantz.eu)