



SR7007 AV RECEIVER



green standby
eco friendly

125w X 7ch

HDAM

HDMI 6+1 in
3 out

4K HD
VIDEO

DSX
AUDYSSEY

Spotify



The first thing to strike you about this all-new AV receiver is the stylish aluminium front panel with illuminated porthole display. It's the perfect reflection of classic Marantz aesthetics. The next thing to strike is the staggering audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail and sensational depth: all thanks to the use of current feedback technology, HDAM pre-amplification and a massively muscled discrete power amplification of 7 x 125W into 8 ohm. What's more, you can enjoy this superior audio performance for all your music sources. The SR7007 has an iPod-digital-compatible USB input and RJ45 network jack. Which means you can connect it to Internet radio, AirPlay, music services such as Spotify and last.fm, as well as access your PC-based music library and much more. This is audio superiority for everything. In addition, video signals are also treated with extra loving care via advanced video processing, and 6+1 HDMI inputs, and 2+1 outputs (Dual output for main zone & Multi Zone output). All support 3D and 4k pass through and 4k scaling video.

Other high-performance features include gold-plated RCA & SPKR terminals, Audyssey MultEQ XT setup and Audyssey DSX for the ultimate experience in surround sound. The front digital connectivity (HDMI & USB) makes it particularly friendly for mobile, tablet, iPad/iPhone, camera & camcorder. What's more, the front panel folds up to reveal an additional two-line display. And to get it all up and running effortlessly, there's also improved System Setup with menu assist on overlay.

Main Features

- Discrete power amplification of 7x 125 Watts 8 ohms RMS
- Current Feedback circuitry with Marantz HDAM
- Full 4k compatibility – Scaling – Pass through – GUI overlay
- DLNA1.5 Network audio streaming and Internet radio
- FLAC HD 192/24 and Gapless playback by firmware update
- AirPlay and music service Spotify and last.fm installed
- Audyssey DSX Processing
- Audyssey MultEQ XT Pro, Dynamic EQ and Dynamic Volume
- 6+1 in / 3 out HDMI (3D/ARC/CEC)
- Independent HDMI out for 2nd room
- Front HDMI input for quick connection of tablet, iPad/iPhone, camera, camcorder, etc.
- iPod / iPhone compatible USB input incl. iPad charging
- Multi room/Multi source including HDMI Video
- Easy Remote Control and Marantz Remote App for advanced media browsing
- Phono MM amplifier

EAN

EU	SR7007/N1B	4951035047484	Black
	SR7007/N1SG	4951035047491	Silver-Gold
UK	SR7007/T1B	4951035047484	Black
	SR7007/T1SG	4951035047491	Silver-Gold

www.marantz.eu

because music matters

SR7007

AV RECEIVER



FEATURES	SR7007
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	• / • / • / •
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	• / • / • / •
Audyssey DSX	•
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
NETWORK	
DLNA Certified	• (v1.5)
Network Audio: MP3 / WAV / AAC / FLAC / FLAC 192/24 / WMA	• / • / • / • / • / •
Gapless playback	• (firmware update)
Internet Radio	vTuner
Music service: last.fm* / Spotify*	• / •
Ethernet	•
OTHERS	
Bluetooth audio via RX101	optional
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Auto speaker setup by microphone Audyssey MultEQ XT	• (PRO)
Audyssey Dynamic EQ / Dynamic Volume	• / •
Video conversion CVBS > HDMI; Comp > HDMI	•
Analogue to HDMI scaling	up to 4k
HDMI to HDMI scaling	up to 4k
Video processing	•
Picture adjust / Noise reduction	• / •
HDMI path though on stand-by	•
4k video pass through	•
3D video pass through	•
Audio Return Channel	•
On Screen Display: GUI	•
GUI overlay on HDMI	•
Setup Assistant (multilingual)	•
Variable cross over	•
Multiroom zones	2 (1x HDMI video)

* not available in all countries

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	4 / 3
Component In / Out	3 / 1
HDMI In / Out	6+1 / 3
AUDIO	
Analogue In / Out	6 / 2
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out	• (7.2)
Subwoofer Out	2
7.1 multichannel input	•
Phono MM	•
OTHERS	
M-XPort for RX101	•
Speaker A / B	•
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting) / Speaker C	• / •
Multi-Room Speaker Terminal	•
Height Speaker Terminal	•
Marantz remote bus	•
IR Flasher In	•
Network: (IP-control / update)	• / •
RS232C (control / update)	• / •
USB firmware update	•
DC Triggers	2
Front Inputs: Audio / Composite / HDMI / USB	• / • / • / •
USB Audio / Made for iPod / Works with iPhone	• / • / •
SPECIFICATIONS	
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	125 W
70% Guarantee	•
Audio Signal to Noise Ratio	100 dB
FM Tuner	•
GENERAL	
Available colors: Black / Silver-Gold	• / •
System Remote Control	RC016SR
Pre-programmed / Learnable / LCD Display	• / • / •
Metal Front Panel	•
Power Consumption in W	660
Standby Consumption in W	0.2
Maximum Dimensions (W x D x H) in mm	440 x 406 x 185
Weight in kg	13.0

Design and specifications are subject to change by Marantz without notice.