marantz®

SR7011
9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

Experience the top of the line Marantz AV Receiver range with the new SR7011. Surround yourself in thrilling 3D surround sound with the most complete immersive format including Dolby Atmos, DTS:X, and Auro 3D (via paid upgrade). All three codecs are able to drive overhead speakers for a true 3D sound experience. And thanks to the receiver's 9 high quality amplifier stages, each providing 125W of pure Marantz power and finesse, you can drive a full 5.1.4 home cinema setup without the need of additional external amplifiers. The SR7011 features high grade audio components that have been carefully selected. The whole internal circuit further enhances audio quality by delicately handling all signals via the Marantz-own HDAMs (Hyper Dynamic Amplifier Module) in Current Feedback topology before passing them on to the power stage to fire up the connected speakers. With built-in HEOS technology, the SR7011 becomes a part of the HEOS wireless multi-room music network that enables you to enjoy your favorite music anywhere and everywhere around your home. You can explore, browse, and play music from your own music library, from online streaming music services as for example Spotify, Deezer, Tidal, and from thousands of internet radio stations using the free HEOS app. And additional Bluetooth and AirPlay let you stream music directly from any compatible device.

Highlights	Your Benefits
• 9.2 channel AV Receiver with 125W per channel (8ohms, 20Hz~20kHz, 0.05%THD)	• Enough power to fill big rooms with renowned Marantz sound
• Dolby Atmos and DTS:X (up to 7.1.4 with an external 2ch amplifer) , Auro-3D upgradeable, 11.2ch Pre-Out	• Immersive 3D sound with effects from overhead
• High performance 192kHz/32bit D/A converters for all channels	• Highest resolution for music and movie sound
• Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ	• Delivering the ultimate equalization for your individual room
• Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	• Improved network stability especially in WiFi-crowded homes
• HEOS Wireless Music Streaming Technology with HEOS App	• Comfortable control options and almost unlimited music sources
• 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020	• Latest HDMI standard for future-proof compatibility
• 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)	• Plenty of inputs for your digital devices; different video in different rooms
• AirPlay, Bluetooth, TuneIn Internet radio, music streaming services such as Pandora, Spotify, SiriusXM, Amazon Prime Music, TIDAL, and more	• Access to almost unlimited online music sources via the HEOS app
• Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	• High Resolution audio streaming for HiFi enthusiasts
• Color-coded speaker terminals, Setup Assistant, Marantz 2016 AVR Remote App	• Hassle-free installation, setup and operation
• Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected	• Audio and video in multiple rooms; ready for 3rd Party Home Automation systems

marantz®

SR7011
9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

FEATURES	SR7011
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
NETWORK / SOURCES	
Network Audio Streaming	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay / Bluetooth audio streaming	• / •
Internet Radio (TuneIn)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud	• / • / • / • / •
Compatible with Remote APP	Android/iOS/Kindle
Ethernet / Wi-Fi	• / • (dual antenna / 2.4/5 GHz)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner / HD Radio	• / • / •
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2 / HDR / BT.2020	• / • / • / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz
INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + 1 zone)

AUDIO			
Analogue In / Out			5+1 / 0
Digital Optical In			2
Digital Coaxial In			2
Multichannel Pre Out			• (11.2 with 11.2 processing)
Zone audio preout			2
Subwoofer Out			2
7.1 Multichannel input			•
SPECIFICATIONS			
Number of poweramps			9
Power Output per channel			
Maximum Power Output Per Channel			235W
6 ohm, 1 kHz, 0.7%, 2ch Drive			165 W
8 ohm, 20 Hz - 20 kHz, 0.05%, 2ch Drive			125W
Audio Signal to Noise Ratio			100 dB
GENERAL			
Available colours: Black			•
System Remote Control			RC031SR
Power Consumption in W			710
Power Consumption No-Sound (ECO ...on/off) in W			65 / 110
Standby Consumption in W			0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) inches			17.3 x 7.3 x 16.2
Weight in lbs			31.1
EAN			
NA	SR7011/U1B	699927150358	Black

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.

|V01|

Design and specifications are subject to change by Marantz without notice.