marantz



NR1200

MARANTZ NR1200 2CH SLIM STEREO RECEIVER

Indulge in high-resolution sonic perfection with the Marantz NR1200 two-channel slim stereo receiver that powers detailed, high-fidelity audio from a compact chassis. At half the height of a traditional receiver, the NR1200 drives impeccable sound for your movies, shows, Hi-Fi audio and more. The NR1200 supports the latest HDMI connectivity with its 5 inputs, each one supporting HDCP 2.3, 4K Ultra HD 60Hz video, HLG and more. Stream music from leading music services and control the NR1200 with voice control compatibility via Amazon Alexa, Google Assistant and Apple Siri.

Highlights

- Slim profile that's half the height of a traditional AV receiver: Delivers exceptional performance and sound quality
- Two-channel discrete power amplifier with separate L/R power amp circuit and power transformer with 75W per channel (8-ohm, 20Hz 20kHz, 0.08% THD)
- Engineered with dedicated Hi-Fi parts for two-channel Hi-Fi performance, including custom designed power capacitors, sound parts exquisitely tuned by sound masters and dual DAC circuit design
- 5 HDMI inputs with full HDCP 2.3 support plus one HDMI out with ARC support for single cable connection with your television
- Speaker A/B, tone control to tune sound to your exact specifications and dedicated dual subwoofer output for evenly dispersed bass, and no audible peaks or dips
- Integrate phono input with HDAM stage to easily connect your turntable
- Auto Low Latency Mode (ALLM) ensures Xbox One users have a more responsive and immersive gaming experience when connected with select TV models
 that also support ALLM
- Control the NR1200 with your TV remote, and HDMI-CEC support for seamless pass-through of picture and audio coding from your TV to the stereo receiver
- High-performance, high-resolution audio playback: Ability to decode high-resolution audio ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz plus, DSD 2.8MHz and 5.6MHz tracks for high-resolution listening
- HEOS Built-in: Enjoy more flexible music streaming in one room or many











































because music matters

marantz

NR1200

MARANTZ NR1200 2CH SLIM STEREO RECEIVER





FEATURES	NR1200
MULTICHANNEL SURROUND	
Max Number of Processing (Preamp) Channels	2.1
NETWORK	
HEOS Multi-Room and Streaming / Network Audio Streaming	0/0
Lossy Formats: MP3 / WMA / AAC	0/0/0
Lossless Formats: FLAC / ALAC / WAV	0/0/0
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	0/0/0
DSD Audio Streaming	up to DSD5.6
Gapless Playback	o (FLAC, WAV ,ALAC ,DSD)
AirPlay2 Audio Streaming	0
Internet Radio (Tune In)	o (Tuneln)
Spotify Connect / Deezer / TIDAL / Napster / Pandora / SiriusXM	0/0/0/0/0/0
Compatible with Remote APP (iOS/Android)	Marantz 2016 AVR Remote
Ethernet / Wi-Fi	o / o (dual antenna/ dual band)
Bluetooth	0
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.3	0/0
eARC (Enhanced Audio Return Channel)	ARC only
GUI Overlay on HDMI	0
HDR / HLG / Dolby Vision	o (HDR10) / o / -
3D Signal Pass-Through	0
HDMI Pass-Through in Standby Mode	0
MULTIROOM / CI	
HEOS Multi-Room Integrated	0
HEOS Link Compatibility: IR/ IP	0/0
IP Control / RS232 Control / Web Control / App Control	0/-/0/0
Domotz Pro / IHIJI compatible	0/0
INPUTS/OUTPUTS	
VIDEO	
HDMI In / Out	5/1
AUDIO	
Analog In / Out	3/-
Phono (MM) In	0
Digital In: Optical / Coaxial	1/1
USB Audio / Made for iPod / Made for iPhone	0/-/-
Multichannel Pre Out	o (2.2)
Subwoofer Out	2

OTHER		
Speaker Terminal: Gold	d Plated Screw / Regular Screw	-/0
Speaker A / B		0
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		-/-/-/0
OTHERS		
FL Display		1 line
Graphic User Interface - GUI		Hybrid GUI
GUI Languages		3
Setup Assistant		0
Smart Select		0
Firmware Update by Network / USB		0/0
Variable Cross Over		0
Optimized Bass Redire	ction	0
ECO Mode		0
Auto Power Off		0
Sleep Timer		0
SPECIFICATIONS		
Number of Poweramps	S	2
Number of Speaker Te	rminals	4
Power Output (8 ohm,	20 Hz - 20 kHz, 0.08% 2ch Drive)	75 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)		100 W
Power Output (6 ohm, 1 kHz, 10% 1ch Drive)		150 W
GENERAL		
System Remote Control		RC041SR
Power Consumption in W		180
Standby Consumption in W		0.2 (with CEC 0.5)
Maximum Dimensio		
Antenna Horizontal: W x D x H (mm)		17.3 x 14.9 x 4.1
Antenna Vertical: W x D x H (mm)		17.3 x 14.9 x 6.9
w/o Antenna: W x D x H (mm)		17.3 x 14.5 x 4.1
Weight (lbs)		18.1
UPC		
NR1200U1B	Black	699927251659

Sound United 1 Viper Way Vista, CA 92081 United States The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, inc. in the United States and/or other countries. The Spotity software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

^{*} All specs can be subject to change.