

# marantz



## SR8015

### Marantz SR8015 11.2ch 8K AV receiver with 3D Audio, HEOS® Built-in and Voice Control

Enjoy exquisitely detailed home cinema with the Marantz SR8015 11.2 channel 8K UHD AV receiver. Delight in the most musical sound for any source — from home theater, to vinyl, to digital streaming. Completely immerse yourself in movies and TV with elevated surround sound formatting from Dolby Atmos®, DTS:X®, DTS:X® Pro, IMAX® Enhanced and Auro-3D®. Enjoy seamless voice control from the leading voice agents, multi-room connectivity and the latest in HDMI technology.

- Premium, power performing amplification: Delivers a masterful 140W per channel (8 ohms, 20Hz-20kHz, THD: 0.05%, 2 ch. driven) so you experience your entertainment in remarkable detail.
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices. Showcasing one dedicated 8K input and two outputs, enjoy 8K/60Hz or 4K/120Hz pass-through in amazing clarity. 8K upscaling is available on all eight HDMI ports.
- Featuring the most advanced object-based audio formats: Dolby Atmos®, Dolby Atmos Height Virtualization Technology, DTS:X®, DTS Virtual:X™, DTS:X® Pro, IMAX® Enhanced and Auro-3D® processing are all supported to allow you to listen to all of your favorite audio styles.
- DTS:X® Pro support: Available in a future firmware update, DTS:X® Pro is capable of processing up to 13 channels, wowing listeners with the most cutting edge DTS technology.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV via eARC HDMI to allow uncompressed and object-based audio formats like Dolby Atmos® and DTS:X® directly from your smart TV app to your AV receiver.
- Bringing you the latest in video compatibility: The latest HDR format support including HDR10, HDR10+ (New in 2020), HLG, Dolby Vision, 4:4:4 color resolution and BT.2020, as well as Dynamic HDR (New in 2020), to provide miraculous picture quality for brightness, clarity and contrast.
- Experience the next scene in movie entertainment: With 8K/60Hz pass-through or upscaling, Dynamic HDR and Quick Media Switching (QMS), enjoy the most crystal clear and smoothest picture quality available.
- The latest in gaming thrills: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), enjoy your gaming experience with amazing imaging with reduced lag and tearing.
- Stream music from your favorite sources: Play songs from Spotify, Pandora, TIDAL and more via AirPlay 2, Bluetooth, Wi-Fi and the HEOS app. (Music streaming services may vary by region)
- Supports all your favorite voice assistants: With the SR8015, simply use your voice to control your preferred voice assistant like Amazon Alexa, Google Assistant, Apple Siri, and Josh.ai for hands free enjoyment.

## Modern Musical Luxury



# SR8015

## Technical Specs



<b>Multichannel surround</b>	
DTS HD Master / DTS:X / DTS:X Pro	• / • / •
DTS Neo:X / DTS Neural:X	- / •
DTS Virtual:X	•
IMAX Enhanced	•
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization	• / • / •
Dolby ProLogic Iiz / Dolby Surround	- / •
Auro 3D	•
Multichannel Stereo	•
Max Number of Processing (Preamp) Channels	13.2
<b>Sound Enhancements</b>	
Discrete Power Amplifier	•
Copper Plated Chassis	•
Power Transformer: Toroidal / EI	Toroidal
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Pure Direct	•
Gold Plated RCA Terminals	•
Clock Jitter Reducer	•
Audyssey	MultEQ XT32
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey LFC	•
Compressed Audio Enhancer: MDAX2	•
<b>Network</b>	
HEOS Multi-room and Streaming	•
Bluetooth Re-transmit for Bluetooth headphones	•
Alexa / Google Voice Assistant / Apple HomePod	• / • / •
Network Audio Sharing	•
Lossy Formats: MP3 / WMA / AAC	• / • / •
Lossless Formats: FLAC / ALAC / WAV	• / • / •
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
DSD Audio Streaming	• (2.8/5.6MHz)
FLAC HD 192/24	•
WAV 192/24	•
ALAC 192/24	•
Gapless Playback	• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	• (AirPlay2)
Internet Radio	• (TuneIn)
Spotify*	• (connect)
Pandora	•
SiriusXM	•
Other Streaming Services *	Amazon Music HD / TIDAL / Deezer / iHeart Radio / Napster / Soundcloud / Mood Mix
Compatible with Remote APP for Smart Phones	Marantz 2016 AVR Remote
Compatible with Remote APP for Tablets	Android / iOS / Amazon Kindle
Ethernet Ports	•
Wi-Fi	•
Bluetooth	•
<b>HDMI</b>	
HDMI Inputs: Back / Front	7 / 1
HDCP2.3 support	•
HDMI Outputs: Main / Zone	2 / 1
Video Conversion Analog -> HDMI	•
Analog to HDMI scaling	480i/576i up to 8K 60/50
HDMI to HDMI scaling	up to 8K 60/50
GUI Overlay on HDMI	•
8K/60Hz / 4K/120Hz	• / •
3D / 4K / CEC / ARC	• / • / • / • / -
Enhanced ARC	•
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	• / • / • / • / •
ALLM (Auto Low Latency Mode) Pass-through for gaming	•
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	• / • / •
3D Signal Pass-Through	•
8K signal pass-through / scaling / GUI overlay	• / • / •
4K Signal Pass-Through / Scaling / GUI Overlay	• / • / •
HDMI Pass-Through in Standby Mode	•
Picture Adjust / Noise Reduction	• / •
CEC	•
DSD Audio Capability	•
Audio Return Channel	•
Auto LipSync	•

<b>Multiroom / CI</b>	
HEOS Multi-Room Integrated	•
HEOS Link Compatibility: IR/ IP	• / •
Multi-Room zones	3
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog	• (2ch) / • (2ch) / • / •
Zone Audio Output: Speaker / Preout	• / •
Zone HDMI Output from HDMI Source	•
IP Control / RS232 Control / Web Control / App Control	• / • / • / •
IR Flasher In	•
Marantz Remote Bus	•
DC Trigger Output	2
HDMI Diagnostics	•
<b>Others</b>	
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32
FL Display	2 lines + Port Hole
Graphic User Interface - GUI	Advanced
ISF Certification	•
GUI Languages	3
Setup Assistant	•
Smart Select	•
Firmware Update by Network / USB	• / •
Variable Cross Over	•
Optimized Bass Redirection	•
Bass Sync	•
ECO Mode	•
Auto Power Off	•
Sleep Timer	•
<b>Video Inputs/Outputs</b>	
Composite In / Out	4+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3
Multi-Room Video Out: Video / HDMI	• / •
<b>Audio Inputs/Outputs</b>	
Analog In / Out	6+1 / -
Phono (MM) In	•
Digital In: Optical / Coaxial	2 / 2
Multi-Room Out: Analog / Digital	2 / -
Multichannel Pre Out	• (11.2)
Subwoofer Out	2 (independent)
7.1 Multichannel Input	•
<b>Other</b>	
Speaker Terminal: Gold Plated Screw / Regular Screw	• / -
Number of Speaker Terminals	13
Speaker A / B	assignable
Bi-Amp Drive	assignable
Multi-Room Speaker Terminal	assignable
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	• / • / - / • / •
USB Audio / Made for iPod / Made for iPhone	• / - / -
AM/FM Tuner	•
<b>General Power</b>	
Number of Poweramps	11
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	140 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)	175 W
Power Output (6 ohm, 1 kHz, 10% 1ch Drive)	250 W
70% Guarantee	•
<b>General</b>	
Metal Front Panel	•
System Remote Control	RC045SR
Pre-Programmed / Learnable / LCD Display	• / • / •
Power Consumption in W	780
Power Consumption No-Sound (ECO on / off) in W	65 W / 110 W
Standby Consumption in W	0.2
CEC Standby Consumption in W	0.5
Network Standby Consumption in W	3.5
<b>Maximum Dimensions</b>	
Antenna/Horizontal:(W x D x H)	17.3 x 18.1 x 7.3
Antenna/Vertical:(W x D x H)	17.3 x 18.1 x 9.8
w/o Antenna:(W x D x H)	17.3 x 17.7 x 7.3
Weight in LBS	38.4

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.