

# marantz®



## NA6006 AUDIOPHILE NETWORK AUDIO PLAYER

Complete your digital audiophile collection with the Marantz NA6006 Network Audio Player. Stream music from Pandora, Spotify, TIDAL and more, and enjoy playback of DSD (2.8/5.6 Mhz), WAV, MP3, AAC, WMA, FLAC and ALAC files. Seamlessly control the NA6006 with your voice and Amazon Alexa when you download the HEOS Home Entertainment Skill.

### Highlights

- Optical and Analog audio output
- Selectable fixed or variable level output
- Headphone output with selectable gain control
- Marantz Music Digital Filtering (MMDF)
- Built-in Bluetooth and Wi-Fi with 2.4GHz/5GHz dual band support
- 1 Optical digital input to connect to your entertainment
- Audiophile 192kHz/24bit D/A conversion (ESS9016) and dual crystal clock for exceptional musical performance
- Marantz proprietary HDAM circuits minimize interference and improve audio
- Enjoy multi-room whole-home audio streaming with HEOS technology
- Amazon Alexa voice control via the HEOS Home Entertainment skill
- Supports DSD (2.8/5.6 Mhz), WAV, MP3, AAC, WMA, FLAC, ALAC file playback via USB devices for high-resolution and Hi-Fi listening
- Stream music from Internet Radio, Spotify Connect, Pandora, SiriusXM, Amazon Music, TIDAL, Deezer and more with Bluetooth, Airplay2 or HEOS built-in



# because music matters

# marantz®

## NA6006 AUDIOPHILE NETWORK AUDIO PLAYER



Design and specifications are subject to change by Marantz without notice.

### FEATURES NA6006

Streaming Engine	HEOS
HEOS Multiroom integrated	•
Voice control using Alexa	•
Wi-Fi	2.4GHz (11b/g/n), 5GHz (11a/n)
Bluetooth	• (SBC, AAC)
Bluetooth Off Mode	•
Airplay 2	•
IP Control	• (via Ethernet)
Wake on LAN	•
Certified Control 4	•
Remote App	• (HEOS)
HDAM version	HDAM & HDAM-SA2
Headphone Amp Gain Control	• (Low/Mid/High)
Headphone Amp	HDAM-SA2 Buffer Full Discrete H/P Amp
Display: Dimmer / Off	• (Dimmer 4-levels)
D/A Conversion	Marantz Musical Digital Filtering (M MDF)
DAC IC	Sabre ES9016K2M
Digital Filter	• (1, 2)

### INPUTS/OUTPUTS

USB	USB-A (Front)
Analog Out	Fixed: 2ch (Gold plated) Variable: 2ch (Gold plated)
Ethernet port	•
Digital Inputs: Coaxial / Optical	0 / 1
Digital Outputs: Coaxial / Optical	0 / 1
Headphone out	• (Front)
Marantz Remote Bus	In / Out

### LOCAL NETWORK MUSIC SUPPORT

INPUT	FORMAT	SAMPLING RATE	BIT LENGTH
Computer music file streaming	MP3	32~48KHz/32~320kbps	—
	WMA	32~48KHz/48~192kbps	—
	AAC	32~48KHz/16~320kbps	—
	WAV	32~192KHz	16, 24bit
	FLAC	32~192KHz	16, 24bit
	ALAC	32~192KHz	16, 24bit
	DSDIFF/DSF	2.8 / 5.6MHz	—

### ONLINE MUSIC SUPPORT

Internet Radio	• (TuneIn)
Cloud Music Service	Spotify Connect Amazon Prime Deezer Premium+
	iHeart Radio, Pandora, SiriusXM

### USB-A

INPUT	FORMAT	SAMPLING RATE	BIT LENGTH
USB-A	MP3	32~48KHz/32~320kbps	—
	WMA	32~48KHz/48~192kbps	—
	AAC	32~48KHz/16~320kbps	—
	LPCM	32~192KHz	16, 24bit
	FLAC	32~192KHz	16, 24bit
	ALAC	32~192KHz	16, 24bit
	DSDIFF/DSF	2.8 / 5.6MHz	

Supported Format	FAT 16/32
------------------	-----------

### GENERAL

Power consumption in W	35W
Standby consumption in W	0.2W
Remote Control	RC005NA
Maximum Dimensions (W x H x D)	17.3 x 4.2 x 14.6 in
Net Weight	14.6 lbs

### UPC

NA6006/U1B	Black	699927370053
------------	-------	--------------

Sound United LLC  
North America Regional Headquarters  
1 Viper Way  
Vista, CA 92081

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.