

Inspired by History...



Driven by Vision.

Are technical accomplishments important in themselves or important for the benefits they bring? Marantz firmly believes the latter and proudly presents the SA-7S1 as a technical tour de force with one goal – to let you hear more musical detail than you thought possible from CDs and SA-CDs. After all, what else is Marantz about?

SUPER AUDIO CD PLAYER



Although most people think of the Marantz heritage as one based on preamplifiers and power amplifiers, remember that Marantz was the first company in the world to announce a Compact Disc player! Since that groundbreaking event, Marantz has led the way in offering advanced digital playback with an unwavering focus on sound quality. The SA-7S1, unabashedly designed for the finest two-channel music reproduction possible, continues that tradition.

- Plays SACD-Stereo, CD, CD-R/RW
- Current Feedback Circuitry
- High-Speed Analog Circuit with HDAM® SA2
- Newly Designed Aluminum Transport
- Digital Isolator for D/A Grounding Separation
- Marantz Original PEC (Phase Error Compensation) PEC777f2
- High Accuracy NPC SM5866A5 D/A Converter
- Low Jitter Internal Clock
- External Clock Input
- Phase Inversion for Balanced Output
- Toroidal power transformer w/Copper Shield Case
- All Copper Plated Chassis w/ Double Layer Bottom



FEATURES

Disc Capacity	1
Multi-ch Capability	-
Playback Formats	SACD-Stereo, CD, CD-R/RW
HDAM	•
Power Transformer	Toroidal
Zero-Impedance Plate	•
Double Layered Bottom Plates	•
Audio DAC	192kHz/24-Bit
Display On/Off	•
Selectable Filters	•
SACD/CD Text	• (SACD)

IN/OUTPUTS

AUDIO	
Analog L&R Out	1/1 (Balanced/Unbalanced)
Analog 5.1ch Out	-
Digital Opt. Out	1
Digital Coax. Out	1
Headphone Out	•
OTHER	
D-Bus Remote (RC-5) In/out	-

SPECIFICATIONS

SACD	
Format	1-Bit DSD
Sampling Frequency	2.8224MHz
Dynamic Range	114 dB
Frequency Response (-3 dB)	2Hz - 50kHz
THD	0.0009%
CD AUDIO	
Format	16-Bit Linear PCM
Sampling Frequency	44.1kHz
Dynamic Range	100 dB
Frequency Response	2Hz - 20kHz
THD	0.002%

GENERAL

Color	Gold
Front Panel	Aluminum
Remote Control	Aluminum Top RC-001SA
Power Requirements	AC 120V 60Hz
Power Consumption	26W
Dimensions W x H x D (Inches)	18" 1/16" x 5 7/16" x 16 13/16"
Weight (lbs.)	49.1



marantz[®]
LIFE AMPLIFIED™

*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.