

# marantz



AMP 30

## AMP 30 6-Channel Power Amplifier

Reference 6-channel, 200-watt-per-channel slimline amplifier featuring Marantz HDAM, Current Feedback Amplification, and balanced line level inputs. Pair with AV 30 to create an exceptional home theater. Combine with additional AMP 30, AMP 20, or AMP 10 power amplifiers to drive more complex speaker configurations.

- **Detailed and immersive sound transforms your home theater**
- **200 watts per channel into 8Ω / 400 watts per channel into 4Ω**
- **Six slimline channels power dedicated home theaters**
- **Bi-amp mode drives high- and low-frequency sections of loudspeakers independently**
- **BTL Mode: Three channels of 400W or six channels of 200W**
- **Balanced XLR input is ideal for reducing input noise**
- **Porthole with analog meter measures output**
- **Soft side lights cast a warm glow on the amplifier front panel**
- **Elegant slimline design matches rich, warm sound**



The Most Musical Sound

# AMP 30

## Technical Specifications

Inputs/Outputs	
Audio	Main Amplifier In
	Balanced & Unbalanced: 6ch (Exclusive use by a selector switch)
Other	Speaker Terminal
	SPKT-1+
	Number of Speaker Terminals
	6
	Bi-Amp Drive / BTL Drive
	Yes / Yes
	Level Meter
Multi-Room	
RS232 Control	Yes
IR Flasher In	Yes
Marantz Remote Bus	Yes
DC Trigger Input / Output	1 / 1
Specifications	
Number of Power Amps	6
Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive)	Normal / BTL
200W / 400W	
Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive)	Normal
400W	
Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive)	Normal
200W	
General	
Front Display	Level Meter
Auto Power Off	Yes
Metal Front Panel	Yes
Power Consumption	300W
Power Consumption, No-Sound (ECO On / Off)	70W
Standby Consumption	0.2W
Maximum Dimensions (W x D x H)	17.4 x 17.4 x 4.4 in.
Weight	22.0 lbs
What's in the Box	Main unit, quick start guide, AC cord, Amp control cable, Remote control cable
UPC Code	747192145699
Limited Warranty (United States and Canada)	5-year



Design and specifications are subject to change by Marantz without notice.

[www.marantz.com](http://www.marantz.com)

