

marantz



MCR 60n DAB

MCR 60n DAB Network Audio Player

Compact All-in-One Hi-Fi System with HEOS®, CD Player, HDMI eARC and MM Phono Stage

- 65W + 65W amplification into 4 ohms
- Powered by HEOS™ multi-room streaming
- HDMI eARC for TV audio integration
- Built-in CD player
- MM phono input for turntables
- Bluetooth RX/TX
- Roon Ready certified
- High-resolution audio up to PCM 384kHz/32-bit
- DSD support up to 11.2MHz
- Optional Dirac Live Room Correction Ready



The Most Musical Sound

MCR 60n DAB

Technical Specifications

Features		
High quality power output	2 × 65W @ 6 ohms / 4 × 33W @ 4 ohms (Speaker A/B)	
CD Compatibility: CD / CD-R/RW / WMA / MP3	Yes / Yes / Yes / Yes	
Tuner: DAB / DAB+ / FM (RDS) / AM	Yes / Yes / Yes / No	
Network audio streaming	Yes	
Spotify Connect* / Tidal* / Deezer* / Amazon Prime Music* / Pandora*	Yes / Yes / Yes / Yes / Yes	
AirPlay 2	Yes	
Roon Ready	Yes	
Internet Radio	Tuneln	
HEOS Multiroom and Streaming	Yes	
Auto Power On by optical input signal	Yes	
Smart Select Buttons	Yes	
Bluetooth / aptX / NFC	Yes / No / No	
Bluetooth Headphone transmission	Yes	
USB Audio: front / rear	No / Yes	
USB-A: DSD / WAV / FLAC / AIFF / ALAC	11.2 / 384 / 384 / - / 384	
Ethernet / WiFi	Yes / Yes	
WiFi setup: WPS / WiFi Sharing	No / Yes	
Lossy formats: MP3 / WMA / AAC	Yes / Yes / Yes	
Lossless formats: DSD / WAV / FLAC / AIFF / ALAC	11.2 / 384 / 384 / - / 384	
Gapless Playback	Yes (FLAC, WAV, DSD)	
Dirac Live Upgradability	Yes	
Tone Control: Bass / Treble / Balance	Yes / Yes / Yes	
Low Noise OLED display	3 line	
Illuminated front	Status LED On / off selectable	
Clock	Yes	
Sleep Timer	Yes	
Programmable Timer: Once / Daily	Yes / Yes	
Inputs/Outputs		
Audio	Analogue In/out	1 / 1
	Digital Optical In/Out	1 / 0
	HDMI ARC input	Yes (HDMI eARC/ARC)
Others	Subwoofer PreOut	Yes
	Main PreOut	AUX assignable
	Speaker Terminal: Push-type / Screw	No / Yes
	Headphone Out	Yes
	Speaker A / B	Yes (individual volume)
	Bi-amping	Yes
	Parallel BTL	Yes
	Powered multi-room for one extra room	Yes

Specifications		
Audio Analog-In	Power Output	2 × 65W @ 6 ohms / 4 × 33W @ 4 ohms (Speaker A/B)
	Number of channels	2 / 4
	Freq. Response (Analogue In)	10Hz - 40kHz
	Signal to Noise Ratio (audio)	90 dB
	Input sensitivity/impedance (Analogue In)	200mV / 30 kohms
	Total Harmonic Distortion 1 kHz, 5 W, 4 Ω / ohms	0.1%
Audio Phono MM	Freq. Response (Phono)	20Hz - 20kHz
	Signal to Noise Ratio (Phono)	74dB
	Input sensitivity/impedance (Phono)	2.5mV / 47 kohms
Tuner FM	Frequency Range FM	87.5 - 108 MHz
	Signal to Noise Ratio (Mono/Stereo) FM	70 / 70 dB
	Total Harmonic Distortion (Mono/Stereo) FM	0.4 / 0.4%
General		
Available colors		Black / Champagne Gold
Remote Control		RC016CR
Power Consumption in W		55
Standby Consumption in W		0.3
DAB antenna included		Yes
Maximum Dimensions (W x D x H) in mm		280 × 303 × 111
Weight in kg		4.2
Carton Maximum Dimensions (W x D x H) in mm		365 × 380 × 230
Carton Weight (inc. product) in kg		5.6
What's in the box (EU)		Main unit, AC cord, remote control, batteries, DAB/FM antenna, quick start guide
EAN code	Black	0747192149451
	Champagne Gold	0747192149468

*Not available in all regions

Design and specifications are subject to change by Marantz without notice.

www.marantz.com

