## marantz

#### SR7011

# 9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY



































Experience the top of the line Marantz AV Receiver range with the new SR7011. Surround yourself in thrilling 3D surround sound with the most complete immersive format including Dolby Atmos, DTS:X, and Auro 3D (via paid upgrade). All three codecs are able to drive overhead speakers for a true 3D sound experience. And thanks to the receiver's 9 high quality amplifier stages, each providing 200 W of pure Marantz power and finesse, you can drive a full 5.1.4 home cinema setup without the need of additional external amplifiers. The SR7011 features high grade audio components that have been carefully selected. The whole internal circuit further enhances audio quality by delicately handling all signals via the Marantz-own HDAMs (Hyper Dynamic Amplifier Module) in Current Feedback topology before passing them on to the power stage to fire up the connected speakers. With built-in HEOS technology, the SR7011 becomes a part of the HEOS wireless multi-room music network that enables you to enjoy your favourite music anywhere and everywhere around your home. You can explore, browse, and play music from your own music library, from online streaming music services as for example Spotify, Deezer, Tidal, and from thousands of internet radio stations using the free HEOS app. And additional Bluetooth and AirPlay let you stream music directly from any compatible device.

### Highlights Your Benefits

9.2 channel AV Receiver with 200W per channel	Enough power to fill big rooms with renowned Marantz sound
Dolby Atmos and DTS:X (up to 7.1.4 with an external 2ch amplifer) , Auro-3D upgradeable, 11.2ch Pre-Out	Immersive 3D sound with effects from overhead
High performance 192kHz/32bit D/A converters for all channels	Highest resolution for music and movie sound
Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ	Delivering the ultimate equalization for your individual room
Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	Improved network stability especially in WiFi-crowded homes
HEOS Wireless Music Streaming Technology with HEOS App	Comfortable control options and almost unlimited music sources
4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)	Plenty of inputs for your digital devices; different video in different rooms
AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer	Access to almost unlimited online music sources
Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming for HiFi enthusiasts
Colour-coded speaker terminals, Setup Assistant, Marantz 2016 AVR Remote App	Hassle-free installation, setup and operation
Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected	Audio and video in multiple rooms; ready for 3rd Party Home Automation systems

www.marantz.eu



## marantz

### SR7011

# 9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY





FEATURES	SR7011
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	•/•/•
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
NETWORK / SOURCES	
Network Audio Streaming	•
Lossy formats MP3 / WMA / AAC	•/•/•
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay / Bluetooth audio streaming	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud	•/•/•/•
Compatible with Remote APP	Android/iOS/Kindle
Ethernet / Wi-Fi	• / • (dual antenna / 2.4/5 GHz)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner	• / •
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2 / HDR / BT.2020	• / • / • / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz
INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3+1 / 2
Component In / Out	3/1
HDMI In / Out	7+1 / 3 (2 main + 1 zone)

AUD	10		
Analogue In / Out			5+1 / 0
Digital Optical In			2
Digital Coaxial In			2
Multichannel Pre Out			• (11.2 with 11.2 processing)
Zone audio preout			2
Subwoofer Out			2
7.1 Multichannel input			•
SPEC	CIFICATIONS		
Number of poweramps			9
Powe	r Output per channel		
6 ohm, 1 kHz, 1%, 1ch Drive			200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive			165 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive		%, 2ch Drive	125 W
Audio Signal to Noise Ratio			102 dB
GENI	ERAL		
Available colours: Black / Silver-Gold			• / •
System Remote Control			RC031SR
Power Consumption in W			710
Power Consumption No-Sound (ECOon/off) in W			75 / 110
Standby Consumption in W			0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm		D x H) in mm	440 x 411 x 185
Weight in kg			14.1
EAN			
EU	SR7011/N1B	4951035058763	Black
	SR7011/N1SG	4951035058770	Silvergold
UK	SR7011/T1B	4951035060162	Black
	SR7011/T1SG	4951035060179	Silvergold

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.eu

<sup>\*</sup> All specs can be subject to change.