

#### CD6007

#### **CD** Player

Combining exclusive Marantz technologies and elegant styling, the CD6007 compact disc player features a reference class 192-kHz/24-bit D/A converter along with our HDAM-SA2 (Hyper Dynamic Amplifier Module) technology to deliver pure sonic performance. The center-mounted CD drive mechanism is compatible with music CD, CD-R and CD-RW discs, while the USB-A port even supports Hi-Res audio such as FLAC HD, DSD and more.

- Versatile playback for all your audio: Easily enjoy your CD and CD-R/RW collection and more through the front USB input.
- Supports all your favorite files: Enjoy all your files through the front USB port including: WAV, MP3, AAC, WMA, FLAC HD, ALAC, AIFF and DSD files.
- Enjoy pristine sound quality from your CD and digital media files: The high quality 192-kHz/24-bit D/A conversion features an IC with two selectable digital filter and accurate system clock.
- Optimized audio reproduction: New selectable two digital filters optimize reproduction of digital music content.
- Engineered for your sound: Further sound tuned with carefully selected components..
- High-quality sound even from demanding headphones: Full discrete headphone amplifier with HDAM-SA2, gain control and the auto off circuit turns off when a
  headphone is not connected to avoid any unwanted interference.
- Eliminate interference for sound purity: Double-layered bottom plate and rigid feet allow for a cleaner more complete sound.
- Best amplifier connection: Gold Plated L/R RCA output for a strong continuous connection to your amplifier.
- Easy to use: System remote controls CD Player, amplifier, and network player.
- Stylish: Available in Black or Silver Gold.

### Modern Musical Luxury







# CD6007

## Technical Specs







1 / / / /
• / • /- / • / • /-
-/-/•/•
-/-/-
-/-/-
HDAM+HDAM SA2
-/•
•
•
•
<u>:</u>
•
•/-
- / • (HDAM-SA2) / -
• / - / -
•
-
-
•
•/•
-
25
•
•
-
2ch
-
-/1
- / 1
-
•
•/-/-
•
-
-
-
-
•
· ·

Specifications	
Mechanism	JTL-101Y
D/A Conversion	Multi-bit, Delta-Sigma
Low Pass Filter stage	HDAM
Output Buffer	HDAM SA2
Headphone amp	HDAM SA2 + OpAmp
SA-CD AUDIO	
Frequency Response (Cust.)	-
Dynamic Range (SA)	-
Signal to Noise Ratio (SA)	-
Total Harmonic Distortion (SA)	-
Channel Separation (SA)	-
CDDA AUDIO	
Frequency Response	2 Hz - 20 kHz
Dynamic Range	100 dB
Signal to Noise Ratio	110 dB
Total Harmonic Distortion	0.002%
Channel Separation	98 dB
General	
Available colors: Gold / Silver / Black / Silver-Gold	-/-/•/•
Metal Front Panel	•
Remote Control	RC004PMCD
Power Consumption in W	32
Standby Consumption in W	0.3
Auto Power Off	•
Detachable Power Cable	•
Maximum Dimensions (W x D x H) in Inches	17.3" x 13.4" x 4.1"
Weight in LBS	14.3
Carton Maximum Dimensions (W x D x H) in Inches	20.4" x 18.4" x 7.4"
Carton Weight (inc. product) in LBS	19.4

Design and specifications are subject to change by Marantz without notice.