## Single Disc CD Player



Want elegant proof that Marantz has never forgotten the audiophile? Just take a look at the CD5003 single disc CD player. It delivers that signature Marantz combination of superb audio performance, refined cosmetics, and surprising flexibility. With circuitry refinements and parts selection directly traceable to our Reference Series and convenience features that make it ideal for both playing and learning music, the CD5003 is all you need to fully appreciate your favorite artists.

- Sophisticated new aluminum/reinforced resin front panel
- Analog audio circuits featuring HDAM®-SA2
- High performance Cirrus Logic stereo D/A converter
- Current-buffered headphone output
- Audio EX mode for super-quiet performance
- MP3/WMA playback capability
- Variable pitch control
- Adjustable Quick Replay
- CD-Text, MP3/WMA tag data display
- Independent gold plated analog output jacks



## Single Disc CD Player

EATURES	
Disc Capacity	1
Playback Formats	CD, CD-R/-RW (CD-DA/MP3/WMA)
Power Transformer	EI
Display Off	•
CD Text	•
Random/Repeat Play	•
Recording Edit Mode	•
AMS (Auto Music Scan) Mode	•
Peak Search	•
Disc Changeable In Play	-
Pitch Control	•
Headphone level Control	•
N/OUTPUTS	
AUDIO	
Headphone Out	•
Analog L&R Out	Independent Gold Plated L&R x1
Digital Optical Out	1
Digital Coaxial Out	1
OTHER	
External Control	Flasher In: 1
O-Bus Remote (RC-5) In/Out	1/1
SPECIFICATIONS	
AUDIO SECTION	
Format	16-Bit Linear PCM, MP3, WMA,
Sampling Frequency	CD:44.1kHz, MP3/WMA:32,44.1,48kHz
Dynamic Range	100dB
Frequency Response	2Hz - 20kHz
THD	2HZ - 2UKHZ
S/N Ratio	0.002%
GENERAL	
TEMPLEMAL	0.002%
Color	0.002%
	0.002% 110dB
Color Front Panel	0.002% 110dB Black Aluminum/Glass-reinforced resin
Color Front Panel	0.002% 110dB Black Aluminum/Glass-reinforced resin
Color Front Panel Remote Control Device	0.002% 110dB Black Aluminum/Glass-reinforced resin e Remote integrated Marantz amp. control function
Color Front Panel Remote Control Device Power Requirement	0.002% 110dB  Black Aluminum/Glass-reinforced resin e Remote integrated Marantz amp. control function AC 120V 60Hz 14W







\*All specifications, dimensions and weights are subject to change without notice.

D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.